

Customer Service: 1-800-653-6556 **or** cs@destinationlighting.com M-F: 7am-5pm **&** Sunday: 11am-4pm **(PST)** 

Lucarne 24V LED Niche Gimbal Down Light in White 2700K by Generation Lighting

# **ITEM 1**



Product Number:	P1524740 or 770119
Manufacturer:	Generation Lighting
Model Number:	95516S-15
Collection:	Lucarne LED Niche
Manufacturer Finish:	White
Total Wattage:	5.5 w.
Voltage Type:	Low Voltage
Voltage Input:	24 v.
Voltage Output:	24 v.
Average Rated Life1:	50,000 hrs
Aspect:	Flat
Dimmable:	With LED / CFL
	Dimmer
Height:	3.50 in.
Width:	2.63 in.
Wattage:	5.5
Bulb Type:	LED
Base Type:	Integrated LED
Number Of Bulbs:	1
Bulb Included:	Yes
EnergyStar Compliant:	No

Recessed Trim Finish:WhiteMaterial:AluminumShipping:UPS RegularCertification Agencies:ETLTrim Style:Eyeball / Gimbal RingCan TrimShape:RoundWet Location:YesDamp Location:YesInstallation Type:RetrofitWeight:0.55 lbsKelvin Temperature:2700Lumens:300Color Rendering Index:90Made In America:NoTitle 24:No

0.0 tototot No rating available

## Item Number: 6VZRFIHD1254D37

### WARNING (To reduce the risk of fire, electric shock, or personal injury):

- 1. We suggest installation by a **licensed electrician**.
- 2. Please read the instruction carefully and save it as you may need it at a later time.
- Before you start, NEVER attempt any work without shutting off the electricity until the work is done.
   A) Go to the main fuse, or circuit breaker, box in your home. Place the main power switch in the "OFF" position.
  - B) Place the wall switch in the "OFF" position.
- 4. Mounting surface should be clean, dry, flat, strong enough and 1/4" larger than the canopy on all sides. Any gaps between the mounting surface and canopy exceeding 3/16" should be corrected as required.
- 5. Make sure that the ceiling or wall can stand the weight of the lamp before installation.
- 6. Make sure the voltage you are using is **120V**. The maximum wattage is **60W** per bulb.
- 7. Keep the lamp away from acidic and alkaline substances in case of damaging the surface of the lamp.
- 8. When replacing bulbs, you should turn off or unplug the lamp and you must wait until it is cool as bulbs get hot quickly.
- 9. The safety instructions appearing in this manual are not meant to cover all possible conditions that may occur. It must be understood that common sense, caution and care must be used with any electrical products.

## **IMAGE FOR FINISHED PRODUCT:**



## TOOLS REQUIRED (NOT INCLUDED):

Before starting assembly and installation please prepare the needed tools as below picture

				Change of Contraction of Contractio
Ladder	Phillips head.flat blade screwdriver	Electrical tape	Pliers	Wire cutter/Stripper



## **ASSEMBLY & INSTALLATION INSTRUCTIONS:**

- 1. Carefully remove the fixture from the carton and check that all parts and accessories are included as shown in the above illustration.
- 2. Turn off power

Before you start the installation, NEVER attempt any work without shutting off the electricity until the work is done.

A) Go to the main fuse, or circuit breaker, box in your home. Place the main power switch in the "OFF" position.

B) Place the wall switch in the "OFF" position.

3. Make assembly



Step A1: Unscrew knob nuts (F) from back plate (E), then set them aside for later installation. Step A2: Carefully pass the supply wires from the outlet box through mounting plate (D). Secure mounting plate (D) to the outlet box with mounting screws (A).

#### Step A3: Make wire connections

#### Connect wires as below wires connection shown. *PLEASE NOTE THAT GROUND WIRE IS* BARE COPPER WIRE, NEVER CONNECT OTHER WIRES TO GROUND WIRES.



# Twist wires together with plastic wire connectors until tightly joined, and wrap each connector with approved electrical tape. Be sure that no wire strands are exposed and then carefully tuck all wires into the outlet box.

Step A4: Align the holes in back plate (E) with the pre-assembled mounting screws, then attach back plate (E) to mounting plate (D) with the previously removed knob nuts (F). Hand tighten until snug.

NOTE: back plate (E) should be snug against the wall with knob nuts (F). If not, remove back plate (E), adjust the threaded length of pre-assembled mounting screws on mounting plate assembly (D) by unscrewing the pre-assembled hex nuts and then screwing the pre-assembled mounting screws in or out of mounting plate (D) until the secure length is achieved. Tighten the pre-assembled hex nuts and back to Step A4.

Step A5: Install the bulb (Not included) (Please do not exceed the maximum wattage recommended on the socket.)

#### 4. Check everything is installed properly, then you could turn on the light. Enjoy!

## CLEANING

To clean, wipe the fixture with a soft cloth. Clean glass with a mild cleaner (such as mild and nonabrasive soap). Do not use abrasive materials such as scouring pads or powders, steel wool or abrasive paper.

## ORDERING PARTS

Keep this sheet for future reference in case you need to order replacement parts. All parts for this fixture can be ordered from the place of purchase. Be sure to use exact wording from illustration when ordering parts.





# Gen 3 Wall Connector Manual

48A Single Phase

Important Safety Information	2
Product Overview	5
Product Specifications	5
Circuit Breaker Rating / Maximum Output	6
Using Wall Connector	8
Features	10
Connectivity	10
Hosted Access Point	10
Local Network	10
Ground Fault Circuit Interruption	12
Ground Assurance	12
Thermal Monitoring	13
Power Outages	3ا 17
Firmware Opdates	13
Wall Connector External Components	14
Wall Connector Internal Components	15
Installation	16
In the Box	16
Tools	17
Installation Considerations	18
Step 1: Prepare Wirebox for Conduit Fittings an Bushings	d 21
Step 2: Prepare Mounting Surface	22
Step 3: Prepare Wirebox and Mount to Wall	23
Step 4: Route Wiring Through Wirebox	24
Step 5: Strip and Land Wiring	25
Step 6: Attach Wall Connector to Wirebox	26
Step 7: Energize Wall Connector	27
Commissioning Procedure	28
Setting Up Access Control	29
Dowor Sharing	71
Power Sharing	JI 71
Power Sharing Overview	اد حت
Considerations for Dower Sharing	ے د حح
Calculating Power Sharing Pequirements for	33
Existing Systems	33
Power Sharing Commissioning Procedure	34
Wall Connector LEDs	36
Light Codes	36
Fault Codes	
Additional Assistance for Red LED Faults	ت ح م
	55
Warranty Information	40
Limits of Liability	41

Dispute Resolution42
----------------------

# **IMPORTANT SAFETY INFORMATION**

Read all instructions before using this product. Save these instructions. Wall Connector features built-in Type B RCD .

This manual contains important instructions for the Tesla Gen 3 Wall Connector that shall be followed during installation, operation, and maintenance. Please review all warnings and cautions before installing and using the Wall Connector.

**WARNING:** When using electric products, basic precautions should always be followed, including the following.

## INSTRUCTIONS RELATING TO RISK OF FIRE OR ELECTRIC SHOCK



**WARNING:** Do not install or use the Wall Connector near flammable, explosive, harsh, or combustible materials, chemicals, or vapors.

WARNING: Turn off power at the circuit breaker before installing or cleaning the Wall Connector.

#### WARNINGS



**WARNING:** This product can expose you to one or more chemicals that are known to the state of California to cause cancer.



**WARNING:** This device should be supervised when used around children.



**WARNING:** The Wall Connector must be grounded through a permanent wiring system or an equipment-grounded conductor.



**WARNING:** Use the Wall Connector only within the specified operating parameters.

**WARNING:** Never spray water or any other liquid directly at the wall mounted control box. Never spray any liquid onto the charge handle or submerge the charge handle in liquid. Store the charge handle in the dock to prevent unnecessary exposure to contamination or moisture.



**WARNING:** Do not use the Wall Connector if it is defective, appears cracked, frayed, broken, or otherwise damaged, or fails to operate.



**WARNING:** Do not use the Wall Connector if the flexible power cord or cable is frayed, broken, or otherwise damaged, or fails to operate.

**WARNING:** Do not attempt to disassemble, repair, tamper with, or modify the Wall Connector. The Wall Connector is not user serviceable. Contact Tesla for any repairs or modification.

**WARNING:** When transporting the Wall Connector, handle with care. Do not subject it to strong force or impact or pull, twist, tangle, drag, or step on the Wall Connector, to prevent damage to it or any components.

## IMPORTANT SAFETY INFORMATION



**WARNING:** Do not touch the Wall Connector's end terminals with fingers or sharp metallic objects, such as wire, tools, or needles.

4

WARNING: Do not insert fingers or foreign objects into any part of the Wall Connector.

**WARNING:** Do not forcefully fold or apply pressure to any part of the Wall Connector or damage it with sharp objects.

**WARNING:** Use of the Wall Connector may affect or impair the operation of any medical or implantable electronic devices, such as an implantable cardiac pacemaker or an implantable cardioverter defibrillator. Check with your electronic device manufacturer concerning the effects that charging may have on such electronic devices before using the Wall Connector.



## CAUTIONS

**CAUTION:** Do not use private power generators as a power source for charging.

**CAUTION:** Incorrect installation and testing of the Wall Connector could potentially damage the vehicle's battery, components, and/or the Wall Connector itself. Any resulting damage is excluded from the New Vehicle Limited Warranty and the Charging Equipment Limited Warranty.



**CAUTION:** Do not operate the Wall Connector in temperatures outside its operating range of -22° F to 122° F (-30° C to 50° C).



**CAUTION:** Ensure that Wall Connector is within storage temperature when moving, transporting, or storing.

# ITEM 3

## **PRODUCT OVERVIEW**

This manual applies to Wall Connectors identified by part number 1457768-\*\*-\*.

## **Product Specifications**

Voltage and Wiring	Nominal 200-240 V AC single-phase
Current Output Range	12 - 48 amps
Terminal Blocks	12-4 AWG (3.5 - 25 mm <sup>2</sup> ), copper only
Supported Conduit Sizing	¾ in (21 mm) default, 1 in (27 mm) optional
Grounding Scheme	TN/TT
Frequency	50/60 Hz
Cable Length	7.3 m (24 ft)
Wall Connector Dimensions	Height: 13.6 in (345 mm) Width: 6.1 in (155 mm) Depth: 4.3 in (110 mm)
Wire Box Bracket Dimensions	Height: 9.8 in (250 mm) Width: 4.7 in (120 mm) Depth: 2.0 in (50 mm)
Weight (including wirebox)	10 lb. (4.5 kg)
Operating Temperature	-22°F to 122°F (-30°C to 50°C)
Storage Temperature	-40°F to 185°F (-40°C to 85°C)
Enclosure Rating	Type 3R
Ventilation	Not required
Means of Disconnect	External branch circuit breaker
Ground Fault Circuit Interrupter	Integrated, no additional required (CCID20)
Wi-Fi	2.4 GHz, 802.11b/g/n
Agency Approvals	cULus - E351001

Transportation and storage: Ensure that Wall Connector is within storage temperature when moving, transporting, or storing.

This device complies with part 15 of the FCC Rules. Operation is subject to the following conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.



## **Circuit Breaker Rating / Maximum Output**

#### **Power Output**

For maximum power output, install a standard double pole 60 amp circuit breaker. Wall Connector includes integrated GFCI protection - **do not install a GFCI circuit breaker**.

Wall Connector incorporates automatic load management, which allows the max output to be customized to an existing power supply. If the electrical supply is unable to support the 60 amp configuration, select a lower amperage configuration.

Circuit breaker (amps)	Max output (amps)	Power output at 240 volts (kW)
60	48	11.5
50	40	9.6
40	32	7.6
30	24	5.7
20	16	3.8
15	12	2.8

**NOTE:** External disconnect switches are neither required nor recommended.

**NOTE:** Circuit breaker size is programmed during the commissioning process. See *Commissioning Procedure on page 28* for details.

**NOTE:** Some Tesla vehicles may draw less current than the max output. Actual charging rate depends on Wall Connector output and onboard charger in the vehicle.

#### **Branch Circuit Conductors and Ground Wire**

- If installing for less than maximum power, refer to local electrical code to select correct conductors and ground wire size that are suitable for the chosen circuit breaker.
- If installing for maximum power, use minimum 6 AWG, 90° C-rated copper wire for conductors.

**NOTE:** Upsize conductors if necessary.

- For sites with multiple Wall Connectors, each Wall Connector must have its own branch circuit with L1, L2/N, and Ground.
- COPPER WIRE TERMINATIONS ONLY for landing in Wall Connector wirebox terminals. Conductors can be stranded or solid.
- Hardwire branch circuits to disconnects or circuit breakers. Do **NOT** install cord-and-plug type connections.
- For outdoor installations, use watertight fittings when securing feeder wires to the wirebox.



#### **Grounding Connections**

Wall Connector must have a ground path back to the main equipment earthing point on site. Without a proper ground connection, the Wall Connector will fault during a ground assurance test. Equipment-grounding conductor must be run with the circuit conductors and connected to the equipment-grounding terminal in the wirebox. Install a ground (PE) wire sized according to local electrical code.



## **Using Wall Connector**

- 1. Open the vehicle charge port by pressing the button on the charge handle, pressing on the charge port door, using the mobile app, using the vehicle touchscreen, or by pressing and holding the trunk button on the keyfob.
- 2. Insert the charge handle into the vehicle charge port.
- 3. Check the vehicle controls to verify charging.
- 4. To remove the charge handle from the vehicle, press and hold the button on the handle to unlock the charge port.

**NOTE:** The vehicle must be unlocked for the charge handle to be removable.



- 5. Remove the charge handle from the vehicle charge port.
- 6. Wrap the charge cable counter-clockwise around the Wall Connector and insert the charge handle into the holster.







## **Features**

### Connectivity

Wall Connector is equipped with Wi-Fi to communicate with local site routers, vehicles, mobile devices, other Wall Connectors, and other Tesla products.



#### **Hosted Access Point**

Wall Connector hosts a WPA2 password-secured, 2.4 GHz, 802.11 Wi-Fi access point network to facilitate commissioning and connecting to other devices.

A unique SSID Wi-Fi network name and WPA2 password for connecting to the Wall Connector are printed on a label at the rear of the main unit, as well as on the front cover of the Quickstart Guide included in the box.



## Local Network

Connecting Wall Connector to a local Wi-Fi network enables it to receive over-the-air firmware updates, remote diagnostics access, and usage data tracking capability. A Wi-Fi connection is required for sites that utilize authentication, billing, and other property management features.

Wall Connector only supports WPA2/3-secured, 2.4 GHz, 802.11 infrastructure mode networks.

NOTE: Networks that are not password protected are not supported. The Wall Connector will not display non-password protected networks in the options list. Open networks without a password are not supported and will not be recognized by the Wall Connector.

**NOTE:** WPA enterprise will be supported in a future firmware update.



**NOTE:** Property management features will be enabled via future firmware updates.



### **Ground Fault Circuit Interruption**

Integrated ground fault circuit interruption (GFCI) protection automatically detects a current mismatch between power delivery conductors that would indicate that current is flowing through the ground (PE) conductor.

If a ground fault occurs after 10 seconds of charging, Wall Connector will wait 15 minutes before automatically re-attempting to charge. Up to four attempts to charge will be made before user interaction is required.

If a residual current fault occurs within 10 seconds of charging, Wall Connector will lock out and user interaction is required to restore charging functionality.

Recommended interaction includes pressing the button on the charging handle, or removing the charging handle from the vehicle and reinserting it. If this does not resolve the issue, look for a ground fault issue such as water ingress.

#### **Ground Assurance**

Wall Connector continuously checks for the presence of a safe ground connection and automatically recovers from faults. Grounded assurance operates by injecting a small amount of current into the ground conductor in order to measure the impedance between line and ground. If high impedance is detected, the Wall Connector will lock out charging and display a fault code of two (2) red blinks. See *Fault Codes on page 38* for a full list of fault codes.

For ground assurance to operate on TN grids, one leg of the distribution transformer must be groundbonded (Neutral). Ground bond should only occur at one location in a site's electrical system.

Wall Connector ground assurance may be adjusted in countries with TT or IT grid configurations and can be disabled in the commissioning procedure.

The Ground Monitor Interrupter feature monitors the Wall Connector ground connection. Select the correct option based on the installation's earthing system and earth impedance.

Depending on country, three options are available:

- Enable: Ground connection will be monitored and a high detected ground resistance will disable the Wall Connector. This is the preferred setting to provide protection, and should be selected where ground connection is expected to be strong (as in the case on TN networks and most TT networks), and where required by regulation.
- **Monitor**: Ground connection will be monitored but a high detected ground resistance will not disable the Wall Connector. This should be selected if the ground monitoring check yields false positives and ground impedance cannot be improved (as is the case in some TT networks).
- **Disabled**: Ground connection will not be monitored. This should be selected where the ground connection is not made (as is the case for IT networks), or where the current induced by this check would be problematic (as is the case on some TT networks with sensitive residual-current devices).

**NOTE:** Ground Monitoring is always enabled for installations in North America.

Temporary problems such as ground faults or utility power surges are resolved automatically.



## **Thermal Monitoring**

Wall Connector actively monitors temperatures in multiple locations while charging to ensure stability of the charge session. Temperature sensors are located at the relays, microcontroller, charge handle, and rear of the main unit to monitor the temperature of the terminals in the wirebox.

In warmer conditions, Wall Connector may reduce current and charge speed to protect itself. When this happens, the light bar on the faceplate will continue to display the "streaming green" and a blink code of three red flashes to indicate that charging has been reduced due to high temperatures. If heat continues to rise, Wall Connector will stop charging and display a blink code of three red flashes.

**NOTE:** See *Fault Codes on page 38* for full list of error codes.

For optimal performance, install Wall Connectors in areas where ambient temperature will remain below 50°C (122°F). In rare circumstances, Wall Connector may begin reducing amperage at 35°C (95°F) ambient temperatures. Adjustments to amperage are automatic and do not require user input; Wall Connector will return to starting current when temperatures are reduced.

#### **Power Outages**

If there is a power outage while Wall Connector is charging a vehicle, charging will automatically resume within 1 to 3 minutes after power restoration. The Wall Connector will display a solid blue light on the faceplate to indicate that it is communicating with the vehicle and waiting to resume charging. Alternatively, pressing the button on the charge handle after power restoration will cause Wall Connector to resume charging immediately.

#### **Firmware Updates**

Firmware updates will be automatically applied to the Wall Connector to improve the user experience and introduce new features. Connect Wall Connector to Wi-Fi for access to the most recent firmware update. See *Commissioning Procedure on page 28*.

Tesla vehicles can provide firmware updates to Wall Connectors.



## Wall Connector External Components

"Wall Connector" refers to the product as a whole.



- 1. Faceplate
- 2. Light bar (vertical)
- 3. Main unit
- 4. Charge handle button
- 5. Charge handle



## Wall Connector Internal Components



- 1. RS-485 port
- 2. Contact blades
- 3. Temperature sensor
- 4. Conductor terminals
- 5. Zip tie anchor
- 6. Sliding contacts
- 7. Wirebox drainage opening (enables Type 3R protection)

## **INSTALLATION**

## In the Box

Main Unit	Wirebox	Wirebox Mounting Template	Hex Bit (4 mm)
Zip tie (x1)	wall Connector-to- Wirebox Fastener (x4)	Wirebox-to-Wall Fastener (x2)	Wilconector         Wilconector         Understand         Outckstart Guide (contains sticker with SSID network name and unique password)         SAVE THIS DOCUMENT
<b>NOTE:</b> The hex bit, zip tie, and fasteners are located in a plastic bag inside the wirebox, which comes attached to the main unit of the Wall Connector.			
<b>NOTE:</b> Wall plugs are not included. If installing in concrete or other like materials, use 6 mm wall plugs.			



## Tools

## **Required Tools**

**NOTE:** Drill bit sizes assume wood mounting surfaces. If installing on concrete or other masonry, consult with an electrician for optimal pilot hole sizes.



#### **Optional Tools**





## Installation Considerations

Wall Connector may be installed on any flat, vertical surface capable of supporting its weight (e.g. wall, pedestal, etc.). Wall Connector weighs .

#### **Choosing Location**

Install Wall Connector in a location that allows the charge cable to reach the vehicle charge port without putting strain on the cable. Recommended installation area for Wall Connectors with 24 ft (7.3 m) cable:



Install Wall Connector in a location with ample clearance on all sides to allow the charge cable to loop around the unit and the charge handle to comfortably land in the side dock.



**NOTE:** If constrained by space, a cable organizer can be installed near the Wall Connector (sold separately).



### **Choosing Height**



- Maximum height (indoor and outdoor): 60 in (1.52 m)
- Recommended height: ~45 in (~1.15 m)
- Minimum outdoor height: 24 in (0.6 m)
- Minimum indoor height: 18 in (0.45 m)

#### **Maximizing Wi-Fi Signal Reception**

Wall Connectors should be connected to a local Wi-Fi network for optimal functionality. For maximum signal reception, avoid installing Wall Connector on opposite sides of concrete, masonry, metal studs, and other physical obstructions that could impede Wi-Fi signal reception.

**NOTE:** If a mobile device is able to connect to local Wi-Fi at a given location, it is a good indication that Wall Connector will also be able to connect.





#### Wire Entry Options



Wall Connector's wirebox has multiple wire entry options. Choose one entry path and follow installation instructions based on chosen entry path.

- 1. Top entry location
- 2. Rear entry locations (left or right)
- 3. Bottom entry location

For additional installation considerations on sites that will have multiple Wall Connectors, see *Considerations for Power Sharing on page 33*.



## **Step 1: Prepare Wirebox for Conduit Fittings and Bushings**

The default conduit size is 3/4 in (21 mm). 1 in (27 mm) conduit is acceptable if needed.

Based on fittings and conduit size, prepare the wirebox.

- For top or bottom entry: Manually remove the conduit plug.
- For rear entry: Drill with 1-1/8 in (29 mm) step bit to prepare wirebox for fittings.

Table 1. For 3/4 in (21 mm) Conduit			
Top Entry	Bottom Entry	Rear Left Entry	Rear Right Entry
		t-1/8 in (29 mm)	1-1/8 in (29 mm)

Table 2. For 1 in (27 mm) Conduit



**NOTE:** For 1 in (27 mm) rear and bottom entry options, drill with 1-3/8 in (35 mm) step bit to prepare wirebox for fittings.



## **Step 2: Prepare Mounting Surface**

1. If applicable, use a stud finder to locate a wooden support stud. Plywood, or other flat wall surfaces capable of supporting the weight of the Wall Connector, may also be used.



2. Based on the chosen wire entry path, position the included cardboard mounting template onto the installation surface and use a 5/32 in (4 mm) bit to drill two pilot holes (one from the top row and one from the bottom row).



**NOTE:** Use a level tool with the cardboard mounting template to ensure a level installation as desired.



#### Drill bit, 5/32 in (4 mm)

Top Entry	Bottom Entry	Rear Left Entry	Rear Right Entry



## **Step 3: Prepare Wirebox and Mount to Wall**

1. Use a 1/4 in (6.5 mm) bit to drill two pilot holes into the wirebox that match the locations chosen on the cardboard mounting template.



Drill bit, 1/4 in (6.5 mm)



2. Attach the wirebox to the mounting location using the included 4 mm hex bit and the two included wood fastener screws.



**NOTE:** Type 3R rating is only possible when washers have sealing gaskets. If mounting to alternate surface (such as a prefabricated pedestal), use alternate fasteners with sealing washers.

**NOTE:** The wood fastener screws are designed to support the weight of the entire Wall Connector, cable, and charging handle.

Ø.



## Step 4: Route Wiring Through Wirebox

1. Route wiring into selected entry point and through the service loop channel on the right side of the wirebox.



2. Use appropriate cable glands, bushings, or fittings to secure the wiring in place and protect from water and debris intrusion.

**CAUTION:** Ensure that bushings are in place to avoid damage to conductors and ground wire when pulled into wirebox.



0

CAUTION: Use copper conductors only.

**NOTE:** Compression-style fittings are recommended to prevent interference.

**NOTE:** For top or bottom wire entry, if installing fittings with a set screw, ensure that the screw is positioned to avoid interference with Wall Connector cables.



## Step 5: Strip and Land Wiring

1. Strip insulation from wires ~1/2 in (~13 mm), route through service channel, and land each wire in its correct terminal block.





2. Secure the wiring in the service channel using the included zip tie.



3. Use a torque driver and the included 4 mm hex bit to torque the terminal screws to 50 lbf . in (5.6 Nm).



**NOTE:** When installing Wall Connector in a split phase electrical system, use Line-to-Line instead of Line-to-Neutral.



## **Step 6: Attach Wall Connector to Wirebox**

1. Attach the main unit to the wirebox by pushing it inward.



2. Secure the main unit to the wirebox with the four included fasteners and the included 4 mm hex bit using a bit driver, applying pressure to the faceplate during the process to compress the internal seal. Firmly hand-tighten the four fasteners until they are secure.



**NOTE:** Do not use a power drill for this step.





## Step 7: Energize Wall Connector

1. Energize the Wall Connector by turning on the upstream circuit breaker.



The Wall Connector's LEDs will turn on. See Wall Connector LEDs on page 36.

2. Proceed with commissioning.

# **COMMISSIONING PROCEDURE**

The commissioning process for Wall Connector enables easy configuration of circuit breaker size, Wi-Fi connectivity, and power sharing options.

- Turn on Wall Connector's corresponding branch breaker to energize the unit. During startup, Wall Connector will display green LEDs for 10 seconds to indicate the maximum circuit breaker it is configured for.
- 2. Use a Wi-Fi-enabled device such as a smart phone to connect to the SSID Wi-Fi signal broadcasted by the Wall Connector. Joining the Wall Connector network can be done by scanning the sticker QR code on the Quickstart Guide cover page, or by manually selecting the network and typing in the WPA2 password (found on the sticker on the Quickstart Guide cover page).



**NOTE:** The Wi-Fi network will broadcast for 15 minutes. To have the Wall Connector broadcast the SSID again, hold the button on the charging handle for 5 seconds or turn the circuit breaker off, then on again.

**NOTE:** If you are unable to connect to the Wall Connector SSID, turn off the cellular data function on your mobile device and try again.

 Scan the QR code below with the device that is connected to the Wall Connector to access the web browser commissioning interface. Alternatively, manually type the URL address (http://192.168.92.1) into the web browser.



4. Follow the onscreen commissioning steps on the web browser to assign Wall Connector to its own circuit breaker and connect it to the local site Wi-Fi network.



**NOTE:** To have the Wall Connector broadcast the SSID again, hold the button on the charge handle for 5 seconds or turn the circuit breaker off, then on again.

## **Setting Up Access Control**

The Charging Access Control feature provides full control over which vehicles are allowed to charge with your Wall Connector and excludes vehicles without access based on user specifications.

1. Sign into the commissioning wizard..

Use the *Commissioning Procedure on page 28* to sign into the commissioning wizard and connect to the Wall Connector Wi-Fi SSID by clicking on the 'Access Control' card.

#### 2. Configure Access Control.

You can choose from three options:

• 'All Vehicles'

This is the default option and will allow charging on all electric vehicles with a matching charge port. To charge with the older generation Tesla Roadster, you will need to pick the 'All Vehicles' option

#### 'Only Tesla'

This option blocks charging on non-Tesla EVs.



• 'Authorized Teslas Only'

This option allows you to add up to 10 specified Tesla cars by their VIN and assign an optional name. For convenience, the VIN of the last 10 cars previously connected to the Wall Connector is made available for selection. The VIN is usually displayed on your windshield and can also be found in the 'Software' tab on your vehicle touchscreen.

# COMMISSIONING PROCEDURE

Authorized Teslas Only	Only Tesla
	Authorized Teslas Only
ou do not have any authorized Teslas. nter a Tesla VIN below and tap the "Add ssla" button.	Authorized Teslas Only
dd a Tesla	Starman's Tesla 🗸 🗸
Select Recently Charged Tesla 👻	SYJYGDEE6KFR00514
	Add a Tesla

## **Power Sharing Overview**

The firmware-based power sharing feature enables up to 6 Wall Connectors installed at the same site to intelligently share the site's total available power via unit-to-unit Wi-Fi. This minimizes the need for many residential and commercial applications to have specific electrical upgrades for concurrent multi-vehicle charging.

During the commissioning process,

- Wall Connectors are allocated to individual branch circuits (each up to 60 amps)
- Total power is allocated to the group of linked Wall Connectors

**NOTE:** For instructions to commission Wall Connectors in a power sharing network, see *Gen 3 Wall Connector Power Sharing*.

Total current output of Wall Connectors that share power will never exceed the site's total allocated power.



- 1. AC feed (service panel)
- 2. Power sharing via Wi-Fi communication



## **Breaker and Branch Circuit Setup**

Power sharing circuits may be installed in an electrical panel that supports other loads. If space is limited or the main power supply is far from the Wall Connectors, installing a dedicated load center may be prudent.

See below for examples of Wall Connector power sharing diagrams (one with sub-panel and one without). Each individual Wall Connector in below examples is capable of providing 48 amps when it is the only one in use. As more Wall Connectors begin plugging into vehicles, the system will automatically distribute power based on the total power allocated to the site.

#### **Power Sharing Setup with Sub-Panel**



- 1. Wall Connector
- 2. 60 A branch circuit
- 3. 100 A sub-panel / feeder breaker

#### **Power Sharing Setup Without Sub-Panel**



- 1. Wall Connector
- 2. 60 A branch circuit



## **Considerations for Power Sharing**

Wall Connector power sharing is achieved wirelessly.

For optimal performance, Wall Connectors within a power sharing network should be installed within view of each other whenever possible.

**NOTE:** Line of sight is recommended but not required. Wireless communication is capable of reaching around concrete corners but network range may degrade as a result.

Avoid placing Wall Connectors on opposite sides of concrete, masonry, metal studs, and other physical obstructions that would impede Wi-Fi signal strength.

**NOTE:** If a mobile device is able to connect to the Leader Wall Connector Wi-Fi, it is a good indication that the Follower Wall Connector will also be able to connect.

## **Calculating Power Sharing Requirements for Existing Systems**

To calculate power supply requirements per number of Wall Connectors for existing electrical systems, use the following equation:

Available continuous amperage:	Number of Wall Connectors:	Max amperage output per Wall Connector when 100% utilized:
	÷	=

**NOTE:** Maximum number of Wall Connectors for power sharing is 6.

**NOTE:** When calculating maximum amperage per Wall Connector, 100% utilization must be greater than 6 amps for power sharing operation. If maximum amperage is greater than 48 amps, power sharing is not necessary.

For large scale sites, consider expected parking time in relation to a 100% utilization rate.

Expected Park Time (hours)	Examples	Recommended Amperage per wall Connector at 100% Utilization
6+ (long term)	Long term parking, overnight parking	12+ amps
3-5 (medium term)	Workplace, hospitality	24+ amps
1-2 (short term)	Shopping and dining	32+ amps

**NOTE:** 100% utilization represents the worst case scenario for charging speeds, where the least amount of power would be available for each individual vehicle. In most situations, not all Wall Connectors would be actively charging a vehicle, which enables faster charging for the remaining vehicles.

**POWER SHARING** 

## **Power Sharing Commissioning Procedure**

#### 1. Identify and configure the wall connector.

One Wall Connector will be the designated leader and provide the configuration and controls for all followers. Install and configure the leader first. Follow the process in the *Commissioning Procedure on page 28* to connect and configure the leader.

#### 2. Add up to five additional followers from the lead Wall Connector.

Click on the power sharing card in the commissioning interface and add additional Wall Connectors to form a power sharing network by wirelessly pairing them to the leader.

	() ▲ 192.168.92.1/sharing/ax (1) :
Network Settings	
Adjust settings for the Power Sharing Network. The network must be disabled before you may make any changes.	Add Wall Connector
Power Sharing Settings >	Note: the Wall Connector must be connected to the same WiFi network as this
Max network current: 100A	one.
	SCAN OR CODE
Add Wall Connector	To connect another Wall Connector, take a picture of the QR code sticker on the
3/4 Devices	Quickstart Guide or QR code on the back of the enclosure. Make sure the QR code is in
Network Status	best results.
Connections: 3/3 Current Draw: 0A/100A	ENTER MANUALLY
Active Alerts: O Status: Disabled	To manually connect another Wall Connector, record the Wi-Fi network name and Password provided on the Quickstart Guide or on the
Wall Connector 1 Serial Number: 87519317000055	back of the enclosure.
Current Draw: 0A / 25A	

#### 3. Set network limits.

Once all followers have been added, set the network limit. This is the total current that will be intelligently distributed between all devices that have vehicles charging.

The minimum current limit is 6 amps per Wall Connector. A six-unit network will have a minimum limit of 36 amps.

The maximum network limit is the sum of the nameplate ratings of all units in the network, minus one amp. A six-unit network of single-phase Wall Connectors can have a maximum network limit of 287 amps. If 288 amps or more electrical service is available in this scenario, then all units can charge at full power and power sharing is not needed. Chat with your electrician for further understanding of the maximum network limit.

POWER SHARING

NOTE: In the event that your leader and followers have different circuit breakers, you have to individually connect to each of the followers on different breakers via the Wi-Fi broadcast, and then set the correct breaker limit.

**NOTE:** For example, in a four Wall Connector network with two 60 amp breakers, one 50 amp breaker and one 20 amp breaker where the leader has a 60 amp breaker, individually connect to the Wall Connectors with 50 amp and 20 amp breakers and set their current limit in the commissioning interface using the *Commissioning Procedure on page 28*.

#### 4. Enable power sharing network.

Once your power sharing network is fully established (followers paired and network limit set), you will have the ability to enable the network.

▲ 192.168.92.1/sharing 11 :	☆ ▲ 192.168.92.1/sharing □ :
Power Sharing Power Sharing network is disabled. Enable in the Network State section.	Power Sharing Wall Connectors can be linked together in a network to allow for power sharing.
Network State	Network State
Power Sharing can be disabled for maintenance, or due to faults or errors within the network settings.	Power Sharing can be disabled for maintenance, or due to faults or errors within the network settings.
Disabled Enabled	Disabled Enabled
Network Settings Adjust settings for the Power Sharing Network. The network must be disabled before you may make any changes.	Network Settings Adjust settings for the Power Sharing Network. The network must be disabled before you may make any changes.
Power Sharing Settings	Power Sharing Settings >
Max network current: 100A	Max network current: IOOA
Add Wall Connector	Add Wall Connector

**NOTE:** No units in the network will be able to charge the connected vehicles if the power sharing has not been enabled.

Ø.

# WALL CONNECTOR LEDS

## **Light Codes**

#### Startup

Once energized at the circuit breaker, every LED (seven total) on the faceplate will illuminate for up to five seconds.



#### After Startup

After Wall Connector is energized at the circuit breaker, certain green LEDs (depending on the circuit breaker size) will illuminate for 10 seconds. See table below for exact light codes.

			8	ł	0	0
Circuit breaker	60 A	50 A	40 A	30 A	20 A	15 A
Maximum output	48 A	40 A	32 A	24 A	16 A	12 A

**NOTE:** To re-display the green LEDs after the initial 10 seconds, press and hold the charging handle button.

When multiple Wall Connectors are linked for power sharing, the **center blue LED** will illuminate during the 10-second startup window.

#### Other

Standby, waiting to plug in	Charging in progress	SSID broadcasting, ready to commission	Waiting to charge, communicating with vehicle
Top green solid	Every green streaming	Green pulsing	Blue solid

# WALL CONNECTOR LEDS

Standby, waiting to plug in	Charging in progress	SSID broadcasting, ready to commission	Waiting to charge, communicating with vehicle
0		((1))	0

WALL CONNECTOR LEDS

## **Fault Codes**

All red blink codes pause for one second, and then repeat.			
Light Bar	What It Means	Details	
No Lights	Power supply issue, charging disabled	Verify that the power supply is turned on. If the issue persists, have an electrician remove the Wall Connector from the wirebox and confirm that voltage is present at the terminal block using a multimeter. Record the voltage readings for the following: L1 to L2/N, L1 to Ground, L2/N to Ground.	
Solid red	Internal , charging disabled	Turn the circuit breaker off, wait 5 seconds, and turn it back on. If solid red light remains, document part number and serial number, then contact Tesla Energy.	
One (1) red blink	Ground fault circuit interruption due to unsafe current path, charging disabled	Inspect the handle, cable, Wall Connector, and vehicle charge port for damage or signs of water ingress. Have an electrician check that ground is not directly connected to a conductor wire in the branch circuit.	
Two (2) red blinks	Ground assurance fault, high ground resistance detected, charging disabled	Verify that the Wall Connector is properly grounded. The ground connection must be bonded in the upstream power supply for proper operation. Check all physical connections, including the wirebox terminals, electrical panel(s), and junction boxes. In residential power supplies, check the bond between ground and neutral at the main panel. If connected to a transformer, contact the transformer's manufacturer for direction on how to bond the ground connection.	
Three (3) red blinks	High temperature detected; charging limited or disabled	Verify that Wall Connector is connected to Wi-Fi and updated with the latest available firmware for optimal temperature sensing functionality. Check the faceplate and cable handle for excessive warmth. Have an electrician remove the Wall Connector from the wirebox and verify that the conductors used are sized correctly and that the terminal block is torqued to specification.	
Four (4) red blinks	Internet connection lost, online features disabled	Check for objects that could interfere with the area's Wi-Fi signal strength. Confirm that the local Wi-Fi router is operational. If the Wi-Fi password was changed recently, follow the commissioning process on your mobile device to update the Wi-Fi settings.	
Five (5) red blinks	Power-sharing communication issue, charging reduced	Check for objects that could interfere with the area's Wi-Fi signal strength. Follow the commissioning process on your mobile device to re-link the Wall Connectors for power-sharing.	
Six (6) red blinks	Overvoltage or poor grid quality detected, charging disabled	Verify that the power supply is nominal 200-240 volts. If the issue persists, have an electrician remove the Wall Connector from the wirebox and confirm that voltage readings are as expected at the terminal block using a multimeter. Record the voltage readings for the following: L1 to L2/N, L1 to Ground, L2/N to Ground.	
Seven (7) red blinks	Vehicle overcurrent detected	Reduce the vehicle's charge current setting. If the issue persists and the attached vehicle is manufactured by Tesla, record the vehicle's VIN and approximate time of the fault and contact Tesla. If the vehicle is not manufactured by Tesla, contact the vehicle's manufacturer.	



## Additional Assistance for Red LED Faults

A Wall Connector's alerts are visible in the browser commissioning wizard (for instructions on how to connect to the commissioning wizard, see *Commissioning Procedure on page 28*).

If additional assistance is required, have the following information prepared before contacting Tesla:

- Short video of Wall Connector LED activity during faulted state
- Photo of Wall Connector's part number and serial number (located on the side label)
- Timeframe that the issue was observed
- VIN of vehicle that plugged into Wall Connector at time of faulted state
- Photo of any error messages displayed on the vehicle's screen

Visit tesla.com/support/contact or scan the QR code below to request support.



Optionally, for owner support and issue troubleshooting: (888) 765-2489

For North America Electrician and Installer support: (650) 963-5655

# WARRANTY INFORMATION

Subject to the exclusions and limitations described below, the Charging Equipment Limited Warranty covers the refund, repair or replacement necessary to remedy any manufacturing defects in a Tesla manufactured and supplied Wall Connector that occur under normal personal use for a period of 48 months, or a period of 12 months for normal commercial use<sup>\*</sup>, and a Tesla manufactured and supplied Mobile Connector or charging adapter that occur under normal use for a period of 12 months, starting from the date of invoice to the customer for any charging equipment. Any Tesla manufactured and supplied connector or adapter included in the initial purchase and delivery of a Tesla vehicle by Tesla is covered under the Basic Vehicle Limited Warranty section of the New Vehicle Limited Warranty for 4 years or 50,000 miles (80,000 km), whichever comes first, subject to the terms and conditions of the New Vehicle Limited Warranty.

\*For warranty claims specific to Wall Connectors, "commercial use" means Wall Connectors used for purposes other than charging at a residential single family home for daily personal use, which includes, but is not limited to, charging at hotels, offices, parking lots and complexes (including apartment, condominiums and other multi-family or unit dwellings), and retail and other locations that allow (including by being listed online or publicly) for pay-for-use charging, or are located where users other than the owner could reasonably obtain access to the Wall Connector.

This Charging Equipment Limited Warranty does not cover any damage or malfunction directly or indirectly caused by, due to, or resulting from, normal wear or deterioration, abuse, misuse, negligence, accident, lack of or improper installation, use, maintenance, storage or transport, including, but not limited to, any of the following:

Failure to follow the instructions, operation, maintenance and warnings published in the documentation supplied with your Tesla connector or adapter;

External factors, including but not limited to, objects striking the Tesla connector or adapter, faulty or damaged electrical wiring or connections, external electrical faults, junction boxes, circuit breakers, receptacles or power outlets, the environment or an act of God, including, but not limited to, fire, earthquake, water, lightning and other environmental conditions;

General appearance or damage to paint, including chips, scratches, dents and cracks;

Failure to contact Tesla upon discovery of a defect covered by this Charging Equipment Limited Warranty;

Any repair, alteration or modification to the Tesla connector or adapter or any part, or the installation or use of any parts or accessories, made by a person or facility not authorized or certified to do so; and

Lack of or improper installation, repair or maintenance, including use of non-genuine Tesla accessories or parts.

Although Tesla does not require you to perform all maintenance, service or repairs at a Tesla Service Center or Tesla authorized repair facility, this Charging Equipment Limited Warranty may be voided, or coverage may be excluded, due to lack of or improper maintenance, service or repairs. Tesla Service Centers and Tesla authorized repair facilities have special training, expertise, tools and supplies with respect to Tesla connectors and adapters and, in certain cases, may employ the only persons, or be the only facilities authorized or certified to work on Tesla connectors and adapters. Tesla strongly recommends that you have all maintenance, service and repairs done at a Tesla Service Center or Tesla authorized repair facility in order to avoid voiding, or having coverage excluded under, this Charging Equipment Limited Warranty.



## **Limits of Liability**

This Charging Equipment Limited Warranty is the only express warranty made in connection with your Tesla connector or adapter. Implied and express warranties and conditions arising under applicable local laws, federal statute or otherwise, in law or in equity, if any, including, but not limited to, implied warranties and conditions of merchantability or merchantable quality, fitness for a particular purpose, durability, or those arising by a course of dealing or usage of trade, or any warranties against latent or hidden defects, are disclaimed to the fullest extent allowable by your local law, or limited in duration to the term of this Charging Equipment Limited Warranty. To the fullest extent allowable by your local law, the performance of necessary repairs and/or replacement of new, reconditioned, or remanufactured parts by Tesla for the covered defects is the exclusive remedy under this Charging Equipment Limited Warranty or any implied warranties. To the maximum extent permissible under your local law, liability is limited to the reasonable price for repair or replacement of the applicable Tesla connector or adapter, not to exceed the manufacturer's suggested retail price. Replacement may be made with parts of like kind and quality, including non-original manufacturer's parts, or reconditioned or remanufactured parts, as necessary. This Charging Equipment Limited Warranty covers only parts and factory labor necessary to repair but does not include any on-site labor costs related to un-installing, reinstalling or removing the repaired or replacement charging equipment. Parts repaired or replaced, including replacement of a Tesla connector or adapter, under this Charging Equipment Limited Warranty are covered only until the applicable warranty period of this Charging Equipment Limited Warranty ends, or as otherwise provided by applicable law. Under no circumstances will the original warranty period be extended as a result of your Tesla connector or adapter being repaired or replaced.

Tesla shall not be liable for any defects under this Charging Equipment Limited Warranty that exceed the fair market value of the applicable Tesla connector or adapter at the time immediately preceding the discovery of the defect. In addition, the sum of all benefits payable under this Charging Equipment Limited Warranty shall not exceed the price you paid for the applicable Tesla connector or adapter.

Tesla does not authorize any person or entity to create for it any other obligations or liability in connection with this Charging Equipment Limited Warranty. Subject to local laws and regulations, the decision of whether to repair or replace a part or to use a new, reconditioned or remanufactured part will be made by Tesla, in its sole discretion. Tesla may occasionally offer to pay some or all of the cost of certain repairs that are not covered by this Charging Equipment Limited Warranty, either for specific models or on an ad hoc, case-by-case basis. Tesla reserves the right to do the above at any time without incurring any obligation to make a similar payment to other Tesla charging equipment owners.

To the maximum extent permissible under local law, Tesla hereby disclaims any and all indirect, incidental, special and consequential damages arising out of, or relating to, the Tesla connector or adapter, including, but not limited to, transportation to and from a Tesla Authorized Service Center, loss of the Tesla connector or adapter, loss of vehicle value, loss of time, loss of income, loss of use, loss of personal or commercial property, inconvenience or aggravation, emotional distress or harm, commercial loss (including but not limited to lost profits or earnings), towing charges, bus fares, vehicle rental, service call charges, gasoline expenses, lodging expenses, damage to tow vehicle, and incidental charges such as telephone calls, facsimile transmissions, and mailing expenses.

The above limitations and exclusions shall apply whether your claim is in contract, tort (including negligence and gross negligence), breach of warranty or condition, misrepresentation (whether negligent or otherwise), or otherwise at law or in equity, even if Tesla is advised of the possibility of such damages or such damages are reasonably foreseeable.

Nothing in this Charging Equipment Limited Warranty shall exclude, or in any way limit, Tesla's liability for death or personal injury solely and directly caused by Tesla's negligence, or that of its employees, agents or sub-contractors (as applicable), fraud or fraudulent misrepresentation, or any other liability to the extent the same is proven in a court of competent jurisdiction in a final nonappealable judgment and may not be excluded or limited as a matter of local law.



## **Dispute Resolution**

To the fullest extent allowed by local law, Tesla requires that you first provide written notification of any manufacturing defect within a reasonable time, and within the applicable coverage period specified in this Charging Equipment Limited Warranty, and allow Tesla an opportunity to make any needed repairs before submitting a dispute to our dispute settlement program (described below). Please send written notification on dispute resolution to the following address:

#### Vehicles registered in the U.S.:

Tesla, Inc

3500 Deer Creek Road

Palo Alto, California

Attention: Charging Equipment Warranty Claims

Phone number: 1-877-79-TESLA (1-877-798-3752)

#### Please include the following information:

- Tesla connector or adapter invoice date
- Your name and contact information
- Name and location of the Tesla Store and/or Tesla Service Center nearest to you
- Description of the defect
- History of the attempts you have made with Tesla to resolve the concern, or of any repairs or services that were not performed by Tesla
- In the event any disputes, differences, or controversies arise between you and Tesla related to this Charging Equipment Limited Warranty, Tesla will explore all possibilities for an amicable settlement

#### **Agreement to Arbitrate**

Please carefully read this provision, which applies to any dispute between you and Tesla, Inc. and its affiliates (together "Tesla").

If you have a concern or dispute, please send a written notice describing it and your desired resolution to resolutions@tesla.com.

If not resolved within 60 days, you agree that any dispute arising out of or relating to any aspect of the relationship between you and Tesla will not be decided by a judge or jury but instead by a single arbitrator in an arbitration administered by the American Arbitration Association (AAA) under its Consumer Arbitration Rules. This includes claims arising before this Charging Equipment Limited Warranty, such as claims related to statements about our products.

Tesla will pay all AAA fees for any arbitration, which will be held in the city or county of your residence. To learn more about the Rules and how to begin an arbitration, you may call any AAA office or go to www.adr.org.

The arbitrator may only resolve disputes between you and Tesla and may not consolidate claims without the consent of all parties. The arbitrator cannot hear class or representative claims or requests for relief on behalf of others purchasing or leasing Tesla products. In other words, you and Tesla may bring claims against the other only in your or its individual capacity and not as a plaintiff or class member in any class or representative action. If a court or arbitrator decides that any part of this agreement to arbitrate cannot be



enforced as to a particular claim for relief or remedy (such as injunctive or declaratory relief), then that claim or remedy (and only that claim or remedy) shall be severed and must be brought in court and any other claims must be arbitrated.

If you prefer, you may instead take an individual dispute to small claims court.

You may opt out of arbitration within 30 days after signing this Charging Equipment Limited Warranty by sending a letter to: Tesla, Inc.; P.O. Box 15430; Fremont, CA 94539-7970, stating your name, product, and intent to opt out of the arbitration provision. If you do not opt out, this agreement to arbitrate overrides any different arbitration agreement between us, including any arbitration agreement in a lease or finance contract.

## TESLA

Revision 1.1

# **PROBRITE**®

#### LED Security Flood Light

Catalog No.	: FSNX50-PC-4K-BZ
Туре	: Flood/Wallpack
Project Name	9:
Location	:
Qty	:
Date	:





PROBRITE's incredibly versatile and reliable LED Flood Light with optional wallpack mount kit offers a wide range of outdoor security lighting applications, including landscape lighting, building perimeter lighting, driveway, or even signage lighting. PROBRITE's FUSION X Dark Bronze 45-Watt LED Wall Pack offers 4000K of bright white light and emits 5000 Lumens of brightness, which is powerful enough to illuminate any space. The light comes with two mounting options, wall/eave mount using the mounting plate and swivel knuckle flood mount.



SYSTEM WATTAGE	LUMENS	LPW	CRI	REPLACES (Incandescent)
45W	5000 lm	100 lm/w	>70	350W

#### HOUSING

Die cast aluminum housing with corrosion resistant powder-coated paint finish. It is designed to ensure cooling by natural convection and passive airflow, to let driver perform efficiently

#### **IP RATING & LISTINGS**

LED light engine is weather proof and water tight rated IP65. UL Listed, suitable for Wet Location.

#### OPTICS

Clear polycarbonate lens, does not alter beam and provide focused and clear lighting output.

#### MOUNTING

It can be mount on wall or eave and can also mount on ground as well with swivel knuckle flood mount.

ITEM 4







#### FINISH

Fade, weather, and abrasion resistant, electrostatically applied, thermally cured, triglycidal isocyanurate (TGIC) textured polyester powdercoat bronze paint finish.

#### WARRANTY

Covered by a 5-year limited warranty. See probrite.com/warranty for details.

#### 3500 NW BOCA RATON BLVD 717, BOCA RATON, FL 33431 1-844-507-5651 | support@probrite.com | www.probrite.com



# **PROBRITE**<sup>®</sup>

#### **PRODUCT SPECIFICATION**

Product Dimensions	: 9.90" × 7.79" × 1.85"
Weight	: 1.9 lbs
Lumens	: 5000
LED Wattage	: 45W
Efficacy	: 100
CRI	: >70
Replaces (Incandescent)	: 350W
Mounting	: Wall Mount/Eave Mount
Frequency	: 50-60Hz
THD (Total Harmonic Distortion)	: <20%
PF(Power Factor)	: >0.9
Ambient Operating Temperature	: (-30)~40°C
Input Voltage	: 120-277V
LED Chip	:-
Photocell	: Yes
Driver	: Non-dimming
Standard Lifetime	: 50,000 hrs
Standard Warranty	: 5 Years
Water Proofing Grade	: Suitable for wet location
CCT	: 4000K Bright White Light
Certifications	: IP 65, Energy Star, FCC Certified, UL Certified
	★

4000K

5000K

SUGGESTED MOUNTING HEIGHT: 6-12 FT.(1.8-3.7 M)

3000К 3500К

#### 3D PHOTOMETRIC VIEW

2700K



#### PRODUCT LINE DRAWING





#### APPLICATION

SUITABLE FOR MULTIPLE APPLICATIONS SECURITY • GENERAL LIGHTING • ENTRYWAYS • DRIVEWAYS • BACKYARDS • SIGNAGE







#### 3500 NW BOCA RATON BLVD 717, BOCA RATON, FL 33431 1-844-507-5651 | support@probrite.com | www.probrite.com

#### Item Number: NA7NNFHD1254P47

#### WARNING (To reduce the risk of fire, electric shock, or personal injury):

- 1. We suggest installation by a licensed electrician.
- 2. Please read the instruction carefully and save it as you may need it at a later time.
- Before you start, NEVER attempt any work without shutting off the electricity until the work is done.
   A) Go to the main fuse, or circuit breaker, box in your home. Place the main power switch in the "OFF" position.
  - B) Place the wall switch in the "**OFF**" position.
- 4. Mounting surface should be clean, dry, flat, strong enough and 1/4" larger than the canopy on all sides. Any gaps between the mounting surface and canopy exceeding 3/16" should be corrected as required.
- 5. Make sure that the ceiling or wall can stand the weight of the lamp before installation.
- 6. Make sure the voltage you are using is **120V**. The maximum wattage is **Type A,Max 60W** per bulb.
- 7. Keep the lamp away from acidic and alkaline substances in case of damaging the surface of the lamp.
- 8. When replacing bulbs, you should turn off or unplug the lamp and you must wait until it is cool as bulbs get hot quickly.
- The safety instructions appearing in this manual are not meant to cover all possible conditions that may occur. It must be understood that common sense, caution and care must be used with any electrical products.

## **IMAGE FOR FINISHED PRODUCT:**



# ITEM 5

## TOOLS REQUIRED (NOT INCLUDED):

Before starting assembly and installation please prepare the needed tools as below picture

				Contraction of the second seco
Ladder	Phillips head.flat blade screwdriver	Electrical tape	Pliers	Wire cutter/Stripper

## PARTS TYPE & QTY INCLUDING:

- (C) Single bar (1)
- (D) Green ground screw (1)
- (E) Canopy (1)
- (F) Collar ring (1)
- (G) Collar loop (1)
- (H) Quick link (2)
- (I) Chain (1)
- (J) Loop (1)
- (K) Lid (1)
- (L) Glass shade (4)

## ACCESSORIES & QTY ENCLOSED:

- (A) Wire connector (3)
- (B) Mounting screw (2)



## **ASSEMBLY & INSTALLATION INSTRUCTIONS:**

- 1. Carefully remove the fixture from the carton and check that all parts and accessories are included as shown in the above illustration.
- 2. Make pre-installation



- Step A1: By measuring, determine the correct number of links needed for proper hanging height. Using the chain pliers, disconnect and discard the unwanted part.
- Step A2: Screw loop (J) onto the top of lid (K). Attach quick link (H) to chain (I) and loop (J) on the top of lid (K).
- Step A3: Carefully weave the fixture wires through chain (I) in and out of every other link and stop just when you reach the top of chain (I). Gently pull the wires to ensure the wires are not stressed.

## 3. Turn off power

Before you start the installation, NEVER attempt any work without shutting off the electricity until the work is done.

A) Go to the main fuse, or circuit breaker, box in your home. Place the main power switch in the "OFF" position.

B) Place the wall switch in the "OFF" position.

## 4. Make installation



- Step B1: Remove collar ring (F) from collar loop (G). Attach single bar (C) to the outlet box with mounting screws (B).
  Note: the side of single bar (C) marked "GND" must face out.
- Step B2: Raise canopy (E) over collar loop (G) and screw collar ring (F) to measure a proper position. **NOTE:** canopy (E) should be snug against the ceiling and collar loop (G) should be screwed enough threads (no less than 6 threads) on the pre-assembled threaded nipple for more secure hanging. If not, adjust collar loop (G) on single bar assembly (C) by screwing collar loop (G) in or out of single bar (C) until the secure length is achieved.
- Step B3: Pass chain (I) through collar ring (F) and then through canopy (E).
- Step B4: Open quick link (H), attach quick link (H) to collar loop (G). Close quick link (H). Pass the fixture wires through collar loop (G) to the top of the pre-assembled threaded nipple and gently pull to ensure the wires are not stressed.

Step B5: If needed, shorten the length of fixture wires. At this point, the remaining wire length measured above single bar (C) is at least 6".

Step B6: Make wire connections

Connect wires as below wires connection shown. *PLEASE NOTE THAT GROUND WIRE IS* BARE COPPER WIRE, NEVER CONNECT OTHER WIRES TO GROUND WIRES.





## Connect wires according to the below chart

Connect Black or	Connect
Red Supply Wire to:	White Supply Wire to:
Black	White
*Parallel cord ( round & smooth )	*Parallel cord (square & ridged)
Clear,Brown,Gold or Black without tracer	Clear,Brown,Gold or Black with tracer
Insulated wire ( other than green ) with copper conductor	Insulated wire (other than green) with silver conductor
*Note: When parallel wires (SPT I are used. The neutral wire is squar or ridged and the other wire will be shape or smooth (see illus.)	& SPT II) e shaped round in Neutral Wire

# Twist wires together with plastic wire connectors until tightly joined, and wrap each connector with approved electrical tape. Be sure that no wire strands are exposed and then carefully tuck all wires into the outlet box.

- Step B7: Raise canopy (E) to the ceiling and secure canopy (E) in place by tightening collar ring (F) onto collar loop (G).
- Step B8: Install the bulb (not included) (Please do not exceed the maximum wattage recommended on the socket.)

## 5. Check everything is already installed properly, then you could turn on the light. Enjoy!

## CLEANING.

To clean, wipe the fixture with a soft cloth. Clean glass with a mild cleaner (such as mild and nonabrasive soap). Do not use abrasive materials such as scouring pads or powders, steel wool or abrasive paper.

## **ORDERING PARTS.**

Keep this sheet for future reference in case you need to order replacement parts. All parts for this fixture can be ordered from the place of purchase. Be sure to use exact wording from illustration when ordering parts.

#### PRODUCT SPECIFICATIONS

# LED OUTDOOR AREA&SECURITY LIGHTING

# ITEM 6



#### **ADVANTAGES**

- 300 Watt Equivalent
- •50,000 Hours of Continuous Use
- •5 Year Warranty
- Durable All-weather Construction
- Non-motion Security Light
- •80 CRI Provides High Color Quality
- Dusk to Dawn
- Adjustable lamp head
- Multi-Volt
- MCompatible HID Bulb type
- Antique bronze



## DW8899ABZ-B SKU# 1002076258

SPECIFICATIONS	
Model Number	DW8899ABZ-B
SKU	1002086258
OSMID	306179204
Power	46 W
AC Voltage, Frequency	100-277 V, 60 Hz
Color Temp (nom.)	4000K
Operation Temp	-22°F ~ 90°F
CRI	80
Lumen Output (min.)	5200 lm
Lifetime Rating	50000Hrs
Efficacy	113.04 lm/watt

PACKAGING	
Weight (±0.5 lb)	3.13 lbs
Size (L x W x H) (±0.1 in)	12.87in x 5.69in x 13.03in
Box Dimensions	15.31in x 5.67in x 12.87in
Gross Weight	4.17 lbs
UPC	008938106283







#### **INCLUDED IN BOX**

- •LED WALL AREA LIGHT (1)
- MOUNTING HARDWARE (1)
- •INSTRUCTION MANUAL (1)

#### **APPLICATIONS**

Suitable for Wet Location IP65 rated

Contact Information 1-877-527-0313 · WWW.HOMEDEPOT.COM