	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

**For**

**Interconnection Customer: Lansing Community Solar, LLC**

**Applicant: Genie Solar Energy**

**5000 kVA PV Generator System**

**528 Lansingville Rd**

**Interconnection to NYSEG**

**Ithaca Division**


**4303101 Tap Circuit**

**34.5kV Feeder**

---


THIS DOCUMENT AND ANY ATTACHMENTS HERETO ("DOCUMENT") IS MADE AVAILABLE BY NYSEG UPON AND SUBJECT TO THE EXPRESS UNDERSTANDING THAT: (A) NEITHER NYSEG NOR ANY OF ITS OFFICERS, DIRECTORS, AFFILIATES, AGENTS, OR EMPLOYEES MAKES ANY WARRANTY, ASSURANCE, GUARANTY, OR REPRESENTATION WITH RESPECT TO THE CONTENTS OF THE DOCUMENT OR THE ACCURACY OR COMPLETENESS OF THE INFORMATION CONTAINED OR REFERENCED IN THE DOCUMENT, AND (B) NYSEG, ITS OFFICERS, DIRECTORS, AFFILIATES, AGENTS, AND EMPLOYEES SHALL NOT HAVE ANY LIABILITY OR RESPONSIBILITY FOR INACCURACIES, ERRORS, OR OMISSIONS IN, OR ANY BUSINESS OR POLICY DECISIONS MADE BY ANY DIRECT OR INDIRECT RECIPIENT IN RELIANCE ON, THIS DOCUMENT OR THE INFORMATION CONTAINED OR REFERENCED THEREIN; ALL SUCH LIABILITY IS EXPRESSLY DISCLAIMED.

---

	<b>Coordinated Electric System Interconnect Review</b>	DER #19658
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

## Table of Contents

<u>Section</u>	<u>Page</u>
1.0 Introduction	3
2.0 Executive Summary	3
3.0 Company EPS Parameters	4
4.0 Interconnection Customer Site	4
5.0 System Impact Analysis	5
6.0 Mitigations for System Impact Analysis Failures	8
7.0 Conceptual Cost Estimate	9
8.0 Revision History	10

	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

## 1.0 INTRODUCTION

This report presents the analysis results of the NYSEG interconnection study based on the proposed interconnection and design submittal from the Interconnection Customer in accordance with the Company Bulletin 86-01. The intent of this report is to assess this project’s feasibility, determine its impact to the existing electric power system (EPS), determine interconnection scope and installation requirements, and determine costs associated with interconnecting the Interconnection Customer’s generation to the Company’s Electric Power System (EPS). This Coordinated Electric System Impact Review (CESIR) study; according to the New York State Standardized Interconnection Requirements (NYSSIR) Section I.C Step 6; identifies the scope, schedule, and costs specific to this Interconnection Customer’s installation requirements.

## 2.0 EXECUTIVE SUMMARY


The total estimated planning grade cost of the work associated with the interconnection of the Interconnection Customer is REDACTED PROPRIETARY FINANCIAL INFORMATION

The interconnection was found to be feasible by distribution planning with modifications to the existing Company EPS and operating conditions, which are described in detail in the body of this Study.

Transmission Planning does not have any concerns with the installation of this proposed generation at this location.

The ability to generate is contingent on this facility being served by the interconnecting circuit during normal Utility operating conditions. Therefore, if the interconnecting circuit is out of service, or if abnormal Utility operating conditions of the area EPS are in effect, NYSEG reserves the right to disengage the facility.

No future increase in generation output beyond that which specified herein for this interconnection has been studied. Any increase in system size and/or design change is subject to a new study and costs associated shall be borne by the Interconnection Customer. An increase in system size may also forfeit the Interconnection Customer’s existing queue position.

	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

### 3.0 COMPANY EPS PARAMETERS


Substation	N. Lansing
Transformer Name	N/A
Transformer Peak Load (kVA)	N/A
Contingency Condition Load, N-1 Criteria (kVA)	N/A
Minimum Daytime Load (kVA)	N/A
Generation: Total/Connected/Queued (kVA)	5358 / 5358 / 0
Contingency Condition Generation: T/C/Q (kVA)	N/A
Supply Voltage (kV)	34.5
Transformer Maximum Nameplate Rating (kVA)	N/A
Distribution Bus Voltage Regulation	Yes
Transmission GFOV Status	N/A
Bus Tie	none
Number of Feeders Served from this Bus	N/A
Connecting Feeder/Line	4303101
Peak Load on Feeder (kVA)	3,590
Minimum Daytime Load on Feeder (kVA)	339
Feeder Primary Voltage at POI (kV)	34.50
Line Phasing at POI	Three-Phase
Circuit distance from POI to substation	1.335 miles
Distance to nearest 3-Phase (if applicable)	N/A
Line Regulation	Yes
Line/Source Grounding Configuration at POI	Effective
Other Generation: Total/Connected/Queued (kVA)	5358 / 5358 / 0
System Fault Characteristics without Interconnection Customer DG at POI with System Upgrades described in Section 6	
Interconnection Customer POI Location	L-533, P-195
I 3-Phase (3LLL)	3584 Amps
I Line to Ground (3I0)	2504 Amps
Z1 (100 MVA Base)	0.1176 + j0.4648 PU
Z0 (100 MVA Base)	0.3013 + j1.0239 PU

### 4.0 INTERCONNECTION CUSTOMER SITE

The Interconnection Customer is proposing a new Primary Metered Service connection.


This location is presently served via Three-Phase 34.5kV.

The proposed generating system consists of :


	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

## 5.0 SYSTEM IMPACT ANALYSIS

Category	Criteria	Limit	Result
Voltage	Overvoltage	<105% (ANSI C84.1)	PASS
With the addition of the subject generator, the maximum voltage as modeled on the Feeder is 105.83% of nominal, and is not impacted by the proposed DER. No remediation is required.			
Voltage	Undervoltage	>95% (ANSI C84.1)	PASS
With the addition of the subject generator, the minimum voltage as modeled on the Feeder is 91.36% of nominal, and is not impacted by the proposed DER. No remediation is required.			
Voltage	Source Regulation for Reverse Power	<9.4% minimum load criteria	FAIL
The total generation downstream of the source regulation is 10.358MVA. The total minimum load on this source is 0.339MVA. Therefore, the generation to load ratio is 3055%.			
Voltage	Line Regulation for Reverse Power	Minimum load to generation criteria	N/A
Not Applicable			
Voltage	Fluctuation	<3% steady state from proposed generation on feeder	PASS
The greatest steady-state voltage fluctuation on the circuit is 0.22% due to the proposed generation and 0.01% on the substation bus due to the aggregate generation.			
Voltage	Fluctuation	<5% steady state from aggregate DER on substation bus	PASS
The greatest steady-state voltage fluctuation on the substation bus due to aggregate generation is 0.01%.			
Voltage	Regulator Variation	Regulator tap movement >1 position	PASS
The greatest voltage fluctuation seen at the voltage regulation at the source is 0.02V.			
Voltage	Flicker	Screen H Flicker	PASS
With an X/R ratio of 3.95, the Pst for the location with the greatest voltage fluctuation is 0.022 and the emissions limit is 0.350.			
Voltage	Flicker	Aggregate Flicker	PASS
The Pst for the location with the greatest aggregate voltage fluctuation is 0.022 and the emissions limit is 0.900.			
Equipment Ratings	Thermal (Cont. Current)	Thermal limits (assuming no load)	FAIL
The proposed generation exceeds an existing equipment thermal capability. (see failed equipment chart below)			
Equipment Ratings	Withstand (Fault Current)	<90% withstand limits (Distribution Equip.)	PASS
No distribution issues.			


	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

Equipment Ratings	Withstand (Fault Current)	<90% withstand limits (Substation Equip.)	PASS
The additional fault current contribution from the generation does not contribute to interrupting ratings in excess of existing EPS equipment.			
Protection	Unintentional Islanding	Unintentional Islanding Document & Company Guidelines	FAIL
There is a significant risk of unintentional islanding.			
Protection	Protective Device Coordination	Company Guidelines (Dist. Line Fusing)	FAIL
There is 1 existing protective device between the Source and PCC. Distribution line Protection and Coordination must be reviewed, any changes or upgrades will be included in section 6 below.			
Protection	Protective Device Coordination	Company Guidelines (Reclosers and Breakers)	PASS
The proposed interconnection does not pose an issue with protective devices.			
Protection	Fault Sensitivity	Rated capabilities of EPS equipment	PASS
The additional fault current contribution from the generation does not contribute to interrupting ratings in excess of existing EPS equipment.			
Protection	Ground Fault Detection	Reduction of reach >100%	PASS
The Interconnection Customer has proposed a Zig-Zag Transformer with an impedance of 4 ohms and X/R ratio of 4. The Zig-Zag Transformer is within Company Guidelines. The Interconnection Customer will contribute approximately 100 A of 310 current to remote bolted line to ground faults and 100 A to faults at the PCC.			
Protection	Overvoltage - Transmission System Fault	Company 3V0 criteria	PASS
The proposed interconnection does not pose an issue.			
Protection	Overvoltage - Distribution System Fault	<125% voltage rise	PASS
With subject generator interconnected the modeled voltage rise on the unfaulted phases of the system is 105%			
Protection	Effective Grounding	[individual utility specifications]	FAIL
With the subject generator interconnected the modeled R0/X1 is 1.89513 PU and the X0/X1 is 7.57649 PU. See Section 6 Point10.			
SCADA	Required EMS Visibility for Generation Sources	Monitoring & Control Requirements	Needed
The 5 MVA subject generator triggers the requirement for SCADA reporting to the Utility.			

	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

Existing Equipment Rating Analysis Table:

EQUIPMENT	VOLTAGE (kV)	LINE or GISID	POLE	PASS/FAIL
3P_REGULATOR	34.5	532	3	FAIL

	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

## 6.0 MITIGATIONS FOR SYSTEM IMPACT ANALYSIS FAILURES

Detail below is intended to provide sufficient information and clarity to give the Interconnection Customer an understanding to the relationship of costs and scope associated with the DER interconnection and the system modifications due to the DER impact. This included any required EPS equipment upgrades. Where scope items are identified, associated labor, equipment rentals and indirect project support functions (such as engineering and project management) are intended and implied.

1. Each individual PCC location must have the ability to trip offline within 2.0 seconds for the loss of voltage on any one individual phase in order to electrically isolate the DER from the utility at the generator interconnection and must be verified at checkout.
2. The Interconnection Customer is required to comply with the utility’s voltage threshold criteria while operating the generating system. If, after interconnection, the Interconnection Customer cannot meet this requirement the Company reserves the right to disconnect the generation and install voltage regulators on the utility side of the Point Of Common Coupling at the Interconnection Customer’s expense.
3. Any potential manual or automatic switching schemes with other distribution circuits will require the customer to disconnect from the distribution circuit at the customer’s PCC.
4. Protection & coordination is based on only the system-normal circuit configuration, and is not applicable for switching scenarios and ties with other distribution circuits.
5. The requirements for Remote Crediting, or Community Distributed Generation billing are that an hourly interval MV-90 meter be installed which has remote access via a dial-up telephone circuit known as a land line. The installation of the land line is the responsibility of the customer, and the installation of the meter is the responsibility of the utility.
6. Install a new microprocessor-controlled line recloser equipped with directionality on the utility-side of the primary-metered service at the PCC.
7. Any circuit tap, substation, or distribution line regulators, and substation LTC/regulator controls must be either already equipped with or changed out to retrofitted microprocessor controls that will handle reverse power flow and co-generation functionality. These include:

***Control is REQUIRED for the Source Regulation:***

- a. Circuit 4303101 Source Line Regulator at or about L-532, P-3

8. 


<b>Failure(s) Addressed:</b>	DP: Thermal
------------------------------	-------------

  
Upgrade existing 3P\_200 Line regulator at or about Line-532 Pole-3 from 200 A to 418 A.
9. 

<b>Failure(s) Addressed:</b>	SPC: Unintentional Islanding
------------------------------	------------------------------


  
Due to the significant risk of unintentional islanding reclose blocking is recommended.



	<b>Coordinated Electric System Interconnect Review</b>	DER #19658
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

10. **Failure(s) Addressed:** **SPC: Overvoltage – Distribution**

Due to the installation failing the Overvoltage-Distribution System Fault and Effective Grounding Screens the project must be revised such that if the generation site is islanded from the utility the system from the Point Of Interconnection into and through the generation equipment is maintained as effectively grounded. The interconnection is required to meet the grounding requirements as identified in AVANGRID Bulletin 86-01 section 6.2.2.2 Grounding. A PE stamped revised 3 Line will be required to be submitted to the [Distributedgenerationadmin@avangrid.com](mailto:Distributedgenerationadmin@avangrid.com) mailbox clearly identifying the revision(s) made to meet the effective grounding requirements. It is vital that the proposed interconnection maintain an effectively grounded system such that during any case of islanding (intentional or not), the circuit (and load) remains effectively grounded. Therefore, verification by the utility of the system meeting the effective grounding requirements is necessary in order to energize the generation site.

	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

## 7.0 CONCEPTUAL COST ESTIMATE

The following items are a good faith estimate for the scope and work required to interconnect the project estimated under rates and schedules in effect at the time of this study in accordance with the most recent version of the NYSSIR.

### Planning Grade Estimate

#### Project #19658


**Scope:**

- A . Install Interconnection PCC Recloser with SCADA & reclose blocking capabilities
- B . Install 3P\_200 Regulator at L-532 P-3 from 200 A to 418 A
- C . Primary metering installation
- D . Engineering support
- E . Project Administration



**Notes to Developer:**

Developer is required to pay all actual costs for system upgrades and interconnection facilities.

	<b>Coordinated Electric System Interconnect Review</b>	<b>DER #19658</b>
	<b>Distributed Energy Resources - NYSSIR</b>	Revision 0 11/18/2022

Notes:

- 1.) These estimated costs are based upon the results of this study and are subject to change. All costs anticipated to be incurred by the Company are listed.
- 2.) The Company will reconcile actual charges upon project completion and the Interconnection Customer will be responsible for all final charges, which may be higher or lower than estimated according to the NYSSIR I.C step 11.
- 3.) This estimate does not include the following:
  - additional interconnection study costs, or study rework
  - additional application fees,
  - applicable surcharges,
  - property taxes,
  - future operation and maintenance costs,
  - adverse field conditions such as weather and Interconnection Customer equipment obstructions,
  - extended construction hours to minimize outage time or Company's public duty to serve,
  - the cost of any temporary construction service, or
  - any required permits.
- 4.) Cost adders estimated for overtime would be based on 1.5 and 2 times labor rates if required for work beyond normal business hours. Per Diems are also extra costs potentially incurred for overtime labor.

## 8.0 REVISION HISTORY

<u>Revision</u>	<u>Date</u>	<u>Description</u>
0.0	11/18/2022	Original